



## LOGIC 40 R A 93015 INOX

13957 9310 INOX

ERHÄLTICH IN  
ROSTFREIER STAHL 13957 9310 INOX



 [Auf der Website anzeigen](#)



Allgemeine Information	
<b>ANWENDUNGSBEREICH</b>	aussenbereich
<b>INSTALLATION</b>	Boden Einbau
<b>FORM / GRÖSSE DES AUSSCHNITTS (MM)</b>	rund - 43
<b>EINBAUTIEFE (MM)</b>	70
<b>SCHUTZ GEGEN EINDRINGEN</b>	IP67
<b>SCHUTZ GEGEN MECHANISCHE EINWIRKUNGEN</b>	IK08
<b>GEWICHT (KG)</b>	0.4
<b>VERSTELLBARKEIT</b>	nicht verstellbar
<b>INFORMATION</b>	REFLECTOR SP-15° INCL.1 x CABLE H05 RN-F 2 x 1mm <sup>2</sup> 0,5m EXCL.LED POWER SUPPLY 350mA-DC IEC 60598-2-13 : max.150kg 25N/cm <sup>2</sup> ESG 6mm

Elektrische Informationen	
<b>KLASSE</b>	III
<b>ENERGIEKLASSE</b>	F

Lichtquelle Info	
Lightsource Name	LED
Lichtquelle	LED array 3,9W / CRI>90 (R9: 55) / 3000K / 385lm
TM-30	Rf: 92 / Rg: 98
SDCM	SDCM2
Risikogruppe	RG2 (threshold 0,6m)
LM80	L90B10 > 41000
LED -Technik (Lichtquelle)	385lm // 3,9W // 98lm/W
LED -Technik (Leuchte)	186lm // 4W // 42lm/W

Erforderliches Zubehör	
LED POWER SUPPLY 350mA-DC DIM	

Optionen	
LOGIC 40 BOX R	
CBOX	
IP68 CONNECTION KIT	
IP68 CONNECTOR 3P	

 DELTALIGHT®

## **LOGIC 40 R A 93015 INOX**










13957 9310 INOX

Detaillierte Installationsanweisungen finden Sie in der Montageanleitung: [13957\\_XXX0\\_HAND.pdf](#)

**LOGIC 40 R A 93015 INOX**


13957 9310 INOX

**SPEZIFIKATION FERTIGSTELLEN**

LED Betriebsgeräte	#
 <p><b>300 48 350 ED1</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1</p>	1->3 <input type="checkbox"/>
 <p><b>300 48 350 ED5</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5</p>	1->3 <input type="checkbox"/>
 <p><b>300 48 350 MDL</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL</p>	1->3 <input type="checkbox"/>
 <p><b>300 48 350 WDL</b> LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL</p>	1->3 <input type="checkbox"/>
 <p><b>300 90 61</b> LED POWER SUPPLY MULTI-POWER DIM6</p>	1->3 <input type="checkbox"/>
 <p><b>300 90 63</b> LED POWER SUPPLY MULTI-POWER DIM9</p>	1->6(6) <input type="checkbox"/>
 <p><b>300 90 64</b> LED POWER SUPPLY MULTI-POWER DIM7</p>	2->4(3) <input type="checkbox"/>
 <p><b>300 90 67</b> LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9</p>	1->3 <input type="checkbox"/>
 <p><b>300 90 68</b> LED POWER SUPPLY MULTI-POWER DIM5</p>	1->4(3) <input type="checkbox"/>

**LOGIC 40 R A 93015 INOX**

13957 9310 INOX



**300 90 69**

LED POWER SUPPLY MULTI-POWER HV DIM9

3->9(9)



**300 90 124**

LED POWER SUPPLY MULTI-POWER DIM7


2->4(3)



**300 90 125**

LED POWER SUPPLY MULTI-POWER MINI DIM5


2->4(3)



**300 90 135**

LED POWER SUPPLY MULTI-POWER HV


5->7



**21012 0010**

LED POWER SUPPLY MULTI POWER


2->3



**21012 0021**

LED POWER SUPPLY MULTI POWER DIM1


2->4



**21012 0035**

LED POWER SUPPLY MULTI POWER DIM5


2->4



**21012 004W**

LED POWER SUPPLY MULTI-POWER WDL


1->6(6)



**21012 005W**

LED POWER SUPPLY MULTI-POWER COMPACT WDL

2->4




**21012 0258**

LED POWER SUPPLY MULTI POWER 200-350 / 10W DIM8

2->2

## LOGIC 40 R A 93015 INOX


13957 9310 INOX



**21012 0268**

LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8


3->3



**21012 0298**

LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8

1->3




**21032 0295**

LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5


1->3

### Bodeneinbaugehäuse




**13910 0010** LOGIC 40 BOX R


### Wasserdichte Verbindungsteile



**216 12 00** CBOX



**216 12 01** IP68 CONNECTION KIT



**216 12 02** IP68 CONNECTOR 3P

 DELTALIGHT®

**LOGIC 40 R A 93015 INOX**

13957 9310 INOX

Notes: