





HELI X SCREEN LED WW A

202 04 22 A

ERHÄLTlich IN
ALU GRAU 202 04 22 A
DUNKELGRAU 202 04 22 N



 [Auf der Website anzeigen](#)

Allgemeine Information

ANWENDUNGSBEREICH	innen-aussenbereich
INSTALLATION	Wand Einbau
FORM / GRÖSSE DES AUSSCHNITTS (MM)	rechteck - 75 x 87
EINBAUTIEFE (MM)	60
SCHUTZ GEGEN EINDRINGEN	IP54
SCHUTZ GEGEN MECHANISCHE EINWIRKUNGEN	IK03
GEWICHT (KG)	0.3
VERSTELLBARKEIT	nicht verstellbar
INFORMATION	EXCL.LED POWER SUPPLY 350mA-DC

Elektrische Informationen

KLASSE	III
ENERGIEKLASSE	E

Lichtquelle Info

Lightsource Name	LED
Lichtquelle	LED cluster 1W / CRI>80 (R9: 6) / 3000K / 132lm
TM-30	Rf: 86 / Rg: 95
SDCM	SDCM3
Risikogruppe	RG2
LM80	L90B10 > 120000
LED -Technik (Lichtquelle)	132lm // 1W // 132lm/W
LED -Technik (Leuchte)	20lm // 1W // 17lm/W

Erforderliches Zubehör

LED POWER SUPPLY 350mA-DC DIM

Optionen

CONCRETE BOX 187

HELI X SCREEN LED WW A










202 04 22 A

Detaillierte Installationsanweisungen finden Sie in der Montageanleitung: [**202_04_22_HAND.pdf**](#)

HELI X SCREEN LED WW A


202 04 22 A

SPEZIFIKATION FERTIGSTELLEN

LED Betriebsgeräte	#
 <p>300 48 350 ED1 LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM1</p>	3->14 <input type="checkbox"/>
 <p>300 48 350 ED5 LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5</p>	3->14 <input type="checkbox"/>
 <p>300 48 350 MDL LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W MDL</p>	3->14 <input type="checkbox"/>
 <p>300 48 350 WDL LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W WDL</p>	3->14 <input type="checkbox"/>
 <p>300 90 61 LED POWER SUPPLY MULTI-POWER DIM6</p>	1->16 <input type="checkbox"/>
 <p>300 90 63 LED POWER SUPPLY MULTI-POWER DIM9</p>	1->25(25) <input type="checkbox"/>
 <p>300 90 64 LED POWER SUPPLY MULTI-POWER DIM7</p>	4->18(15) <input type="checkbox"/>
 <p>300 90 67 LED POWER CONVERTER 24V-DC TO MULTI CURRENT 48W DIM9</p>	3->15 <input type="checkbox"/>
 <p>300 90 68 LED POWER SUPPLY MULTI-POWER DIM5</p>	2->16(15) <input type="checkbox"/>

HELI X SCREEN LED WW A

202 04 22 A



300 90 69

LED POWER SUPPLY MULTI-POWER HV DIM9

8->39(39)



300 90 124

LED POWER SUPPLY MULTI-POWER DIM7


6->17(15)



300 90 125

LED POWER SUPPLY MULTI-POWER MINI DIM5


4->17(15)



300 90 135

LED POWER SUPPLY MULTI-POWER HV


17->29



21012 0010

LED POWER SUPPLY MULTI POWER


6->15



21012 0021

LED POWER SUPPLY MULTI POWER DIM1


4->18



21012 0035

LED POWER SUPPLY MULTI POWER DIM5


4->18



21012 004W

LED POWER SUPPLY MULTI-POWER WDL


1->25(25)



21012 005W

LED POWER SUPPLY MULTI-POWER COMPACT WDL

4->18




21012 0258

LED POWER SUPPLY MULTI POWER 200-350 / 10W DIM8

7->10

HELI X SCREEN LED WW A


202 04 22 A



21012 0268

LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8


10->14



21012 0298

LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8


3->15



21012 0308

LED POWER SUPPLY 350mA / 7,35W DIM8

5->7




21032 0295

LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

3->14



Concrete Box



270 11 187 CONCRETE BOX 187



Notes: